

Quick Guide for Installing Conexant MonoPack-TAM Modem Driver

The CD includes below:

1. \Manual\; Modem manual.
2. \Rwmpci95\; Modem Driver for Windows 95/98.
3. \Rwmpci95\; Modem Driver for Windows NT4.0.
4. \Acrobat\; Acrobat reader.
5. Run "Setup.exe" or "Sv\Picshell.exe" from CD root directory to install SuperVoice or other software.

Quick software installation

Power on your computer and modem, then start Windows 95/98.

Windows 95/98 will detect the modem automatically.

1. Windows 95 B (OSR2):

- 1.1 Please insert the driver CD supplied and click "Next". The message of "PCI Communication Device" will appear. However, it may vary with the type of the mother board.
- 1.2 Windows will find the updated driver for "Conexant PCI Modem Enumerator", then click "Finish".
- 1.3 Click "OK".
- 1.4 Please type D:\RWMPCI95 ("D" is the letter of CD-ROM drive) and click "OK" to find the location of the modem driver and finish the driver installation.

2. Windows 98:

- 2.1 Please insert the driver CD supplied then click "Next". The message of "PCI Communication Device" will appear. However, it may vary with the type of your mother board.
- 2.2 Select "Search for the best driver for your device (Recommended)" and click "Next".

- 2.3 Select Specify a location and type "D:\Rwmpci95" ("D" is the letter of CD-ROM drive) and click "Next".
- 2.4 Windows will find the driver for "Conexant PCI Modem Enumerator", then click "Next".
- 2.5 Click "Finish" to end this installation procedure.

3. Selecting country code

- 3.1 Please go to "Start>Settings>Control Panel", double-click on "System" icon.
- 3.2 Click on "Device Manager" button, select "Conexant HCF 56K Data Fax RTAD PCI Modem" then click "Properties".
- 3.3 Click "Country Select" to select your country from the list and click "Apply". Then click "OK" to end this procedure.

4. Windows NT 4.0

- 4.1 Please insert the CD supplied. Then click "Start \ Run" on the desktop and use "Browse" to open the file of D:\RWMPICINT4\SETUP.EXE. (D is the letter of CD-ROM drive)
- 4.2 Click "Next".
- 4.3 Click "Next".
- 4.4 The message of "The modem driver was installed successfully" will appear, then click "Finish". Note: You must restart your computer to enable the modem driver.
- 4.5 To select your country, please click "Start \Setting \Control Panel" on the desktop and double-click on the "HCF Modem Country Select" icon.
- 4.6 Select your country and click "OK".